



Partner Beyond Technology

### HDS Cluster Configuration Support Matrix For Microsoft Windows Server

Operating System	Storage	Server(s)	Host Bus Adapters	Interconnect FC Switches	Multi-Path Software	Other
Windows Server 2003, Enterprise Edition	Hitachi TagmaStore Adaptable Modular Storage Platform - AMS1000, AMS500 - AMS200, WMS100  Microcode: 0760	Max supported nodes = 8  IBM eServer xSeries - x260, x335, x336, x345 - x346, x365, x366, x460	Emulex LP11002  Driver: 1.20a3 Bios: 1.70a3 FW: 2.10a9	McData Sphereon 4700  Firmware version: 9.01	Hitachi Dynamic Link Manager (HDLM)  Version: 5.8	
Windows Server 2003, Enterprise Edition	Hitachi TagmaStore Adaptable Modular Storage Platform - AMS1000, AMS500 - AMS200, WMS100  Microcode: 0740	Max supported nodes = 8  IBM eServer xSeries - x335, x336, x345 - x346, x365, x366, x445	Emulex LP9802  Driver: 2.30a2 Bios: 1.70a3 FW: 1.91a1	Brocade SilkWorm 200e Firmware version: 5.1.0d	Hitachi Dynamic Link Manager (HDLM)  Version: 5.8	
Windows Server 2003, Enterprise Edition	Hitachi TagmaStore Adaptable Modular Storage Platform - AMS1000, AMS500 - AMS200, WMS100  Microcode: 0720	Max supported nodes = 8  IBM eServer xSeries - x345, x346, x365 - x366, x440, x445	Emulex LP9802  Driver: 1.10a4 Bios: 1.70a3 FW: 1.91a1	Brocade 3250, 3850 3900, 12000, 24000 Firmware version: 4.4.0f  Geo-Cluster: 25km	Hitachi Dynamic Link Manager (HDLM)  Version: 5.7	
Windows Server 2003, Enterprise Edition	Hitachi TagmaStore Adaptable Modular Storage Platform - AMS1000, AMS500 - AMS200, WMS100  Microcode: 0720	Max supported nodes = 8  IBM eServer xSeries - x345, x346, x365 - x366, x440, x445	Emulex LP9802  Driver: 1.10a4 Bios: 1.70a3 FW: 1.91a1	Brocade 3250, 3850 3900, 12000, 24000 Firmware version: 4.4.0f	Hitachi Dynamic Link Manager (HDLM)  Version: 5.7	

\*Note: Servers can be used homogeneously or heterogeneously within a cluster